



Media Processors Simplify Multi-Projection Workflows for Immersive Experiences

ET-FMP50

Media Processors Simplify Multi-Projection Workflows for Immersive Experiences

Key Features

Flexible Design Streamlines Installation

Simple Yet High-Precision Adjustment

Smooth and Continuous Content Playback



ET-FMP50

<https://ap.pnd.panasonic.com/hk/en/et-fmp50>

| | |
|--|--|
| Type | Box-type |
| Terminals -> HDMI™ IN | — |
| Terminals -> HDMI™ OUT | HDMI™ x 4, Audio signal: Linear PCM, 44.1 kHz/48 kHz, 16-bit, 2 channels |
| Terminals -> AUDIO OUT(M3 Stereo Mini Jack) | 3.5 mm stereo mini-jack |
| Terminals -> LAN | RJ-45 x 1 for network connection, 10Base-T/100Base-TX, 1000Base-T,NDI® and Dante® (2 channels)* ¹ compatible |
| Video format | HAP* ³ / H.264, 8-bit, 3840 x 2160 pixels, 60p, YPbPr 4:2:0, 300 Mbps / H.265, 8-bit, 18 million pixels (long side 7680 pixels or less), 60p, (including 7680 x 1920/60p, 4096 x 4096/60p), YPbPr 4:2:0, 300 Mbps |
| Max. video output resolution | 3840 x 2160/60p x 1 or 1920 x 1080/60p x 4* ² |
| Audio format | AAC-LC, 16-bit, stereo |
| Storage | 4 TB |
| Operating system | Linux® |
| Power supply | AC 100–240 V, 50/60 Hz |
| Maximum power consumption | 64 W |
| Dimensions (W x H x D) | Approx. 210 x 44 x 295 mm (8 9/32" x 1 23/32" x 11 5/8") (Excluding feet) |
| Weight | Approx. 2.0 kg (4.41 lbs) (Excluding AC adapter and cord) |
| ENVIRONMENT -> Operating Environment(Temperature) | 0–40 °C (32–104 °F) |
| ENVIRONMENT -> Operating Environment(Humidity) (No condensation) | 10–80 % (no condensation) |
| Footnote Description | <ol style="list-style-type: none"> 1. HAP Q content is not supported. 2. When four HDMI™ outputs are used simultaneously. 3. Compatible with HAP 1 and HAP Q. Please consult the spec file for detailed information. 4. For the ET-FMP20 (512 GB) and ET-SBFMP10 (512 GB), approximately 30 GB of the total storage space is allocated for system usage and is unavailable to the user. 5. The operating temperature range may differ according to the specific projector model paired with the ET-SBFMP10. |